

Load-Bearing Underwater Cable for Hand-Hauled, Real-Time Profiling

Profiling in real time, from small boats not equipped with a winch, calls for hand hauling a CTD using a load-bearing data cable. Sea-Bird can supply cables up to 300 meters (985 feet) in length that provide a practical way to hand-haul SBE 19 / 19*plus* / 19*plus* V2 SeaCAT Profilers or SBE 25 / 25*plus* Sealoggers CTDs, and acquire CTD profile data in real time. In these cases the CTD is powered by its battery, and the cable allows two-way* RS-232 communications (3 conductors - *transmit, receive,* and *common*) and bears the weight of the CTD.

The cable is not intended for static working loads above 45 kg (100 lbs); working loads above 18 kg (40 lbs) may be difficult to handle without a winch. The minimum recommended cable bend radius is 10 cm (4 inches) (e.g., 20 cm sheave block nominal diameter). Use with loads exceeding 45 kg (100 lbs) or cable bend radius less than 10 cm (4 inches) will reduce the cable's useful life and void the warranty.

Attached drawings show the cable assembly and wiring details, and include tables of Sea-Bird part numbers for cables of specific lengths:

- Drawing No. 32284 Standard connector to the CTD and 9-pin connector to the computer
- Drawing No. 32643 Wet-pluggable connector to the CTD and 9-pin connector to the computer
- Drawing 32821 Standard connector to the CTD and 4-pin connector to a SeaCAT / Sealogger RS-232 & Navigation Interface Box (Interface Box PN 90488 or PN 90545)

If the length needed is not listed on the drawing, contact Sea-Bird with the drawing number and desired length (300 meter [985 feet] maximum).



* Notes:

- Communications from the CTD to a computer An SBE 19, 19plus, 19plus V2, 25, or 25plus CTD reliably transmits data over 300 meters (985 feet) of cable to a computer. See the applicable CTD manual for baud rate and real-time output rate limitations.
- Communications **from a computer to the CTD** for instrument setup, data upload, etc. are dependent on the computer serial port hardware and software settings, but are usually reliable over cables up to 300 meters long at low baud rates. Some laptop computers may have inferior serial port hardware, limiting the cable length over which they can transmit. If a computer cannot transmit over a long cable, disconnect the CTD from the long cable and connect to the computer using the shorter I/O cable provided with the CTD.

Using Load-Bearing Cable for Real-Time Data Acquisition with Seasave

- 1. Communicate with the CTD via the terminal program* to set up sampling parameters, initialize memory, etc. (see terminal program Help Files).
- 2. Configure Seasave for real-time acquisition and display (see Seasave Help files).
- 3. Start the CTD sampling via magnetic switch (or with computer command in the terminal program* per CTD manual instructions).
- 4. Deploy the CTD to begin profile.
- 5. Recover the CTD.
- 6. Stop the CTD sampling via magnetic switch (or with computer command in the terminal program*).
- 7. Communicate with the CTD via the terminal program* to upload data.

*Note: Sea-Bird has several terminal programs for communicating with instruments -

- SBE 19, 19plus, and 25: use Seaterm terminal program
- SBE 19plus V2 and 25plus: use SeatermV2 terminal program

Cable Specifications

- Nominal O.D. 7 mm (0.270 in.)
- Twisted trio of 22 awg conductors
- Pressure-extruded polyurethane jacket, dull, non-slip finish
- Weight in air approximately 50 grams/meter (0.034 lbs/ft)
- Weight in water approximately 4 grams/meter (0.0027 lbs/ft)
- PMG-4FS connector with locking sleeve to CTD and DB-9 serial data connector to computer Drawing 32284
- MCIL-4FS wet-pluggable connector with locking sleeve to CTD and DB-9 serial data connector to computer - Drawing 32643
- PMG-4FS connector with locking sleeve to CTD and MS3106A-14S-2P connector to Seacat/Sealogger RS-232 & Navigation Interface Box - Drawing 32821
- Mechanical terminations are *Chinese finger trap* type, made from hollow-core, polypropylene rope with stainless thimbles
- Internal Kevlar braid with 180 kg (400 lb) breaking strength
- Maximum recommended working load 45 kg (100 lbs)
- Minimum recommended cable bend radius 10 cm (4 inches) (e.g., a 20-cm sheave block nominal diameter)



-	BB	STRENGTH CB KLP	GB	- Process Change CB MJ															CONDUCTOR 32 AMC				8		FLECTRONICS. INC		NTS APPROVED BY	PMG-4FS to DB-9S
3.02 A Redrawn on new template 06.02 B Add 17097, Step 5	00	9.23.02 D ADU. GIY & LENGIH 10.11.02 E CHANGED BREAK STRENGTH	F ECN 971	9.6.2006 G ECN 991 - Proce						Ę		P2		DB-95, SBE PN 17096 HOOD, SBE PN 17097			CABLE TYPE: FALMAT	SBE FN 1/1203, FIGTURE PER UNG 322/3	FM020999SA1 REV, B POLYTIPETHANE KEVI AP REINEAPCED 3 1	YELLOW JACKET, NOMINAL O.D. = 0.270 IN.	100 LBS. WORKING LOAD (45 Kg)	+ INCLI MINIMUM BEIND INVITED (10 CITI)			TOLERANCES SFA-BIRD FL	- I	DECIMAL TITLE LOOD BECIMAL	
										H					DIM C	20 FT	6 FT	20 FT	20 FT									
P2 DB-9S	PIN 5	PIN 3	PIN 2	1				()	/				•-©		DIM B	52 IN	52 IN	52 IN	52 IN									
ALT COLOR	WHITE	BLACK	RED					ibly (2 eact		-20" +/- 2"-	: [\bigotimes	-@		A M	236 m	E Q	76 m	70 m									
			ED		A			ice Assem		,		20			DIM	775 FT	20 FT	250 FT	230 FT									
S COLOR	WHITE	WHITE/BLACK	WHITE/RED	I	DIM			6, Eye Spl			i	X	•-@	۵.	PIGTAIL	172476	172546	172547	172602									
P1 PMG-4FS	PIN 1	PIN 2	PIN 3	PIN 4				SBE PN 801676, Eye Splice Assembly (2 each)		-"0 -/+ "00			•	SLEEVE G-FLS-P	SBE PN	801833 1	801885 1	801886 1	801910 1				5					
		31568	PLICES					Ĺ			Ø	1			DIM C	20 FT	20 FT	20 FT	20 FT	20 FT	20 FT	20 FT	20 FT	20 FT	20 FT	20 FT	20 FT	20 FT
		JBING 3", PN .	ING BRAIDED S				A			7				PMG-4FS W/ LOCKING	DIM B	52 IN	52 IN	52 IN	52 IN	52 IN	52 IN	52 IN	52 IN	52 IN	52 IN	52 IN	52 IN	52 IN
ALLATION	TH BRAID	ADHESIVE TU	AFTER INSTALL								ſ			PI	A	60 m	182 m	30 m	100 m	152 m	50 m	125 m	25 m	300 m	160 m	20 m	200 m	40 m
FT-EYE INST	BRING CABLE THROUGH BRAID A + / - 2 INCHES REHIND EVE	IA. HEATSHRINK	CONNECTOR /												DIM	200 FT	600 FT	100 FT	330 FT	500 FT	165 FT	415 FT	83 FT	985 FT	528 FT	66 FT	660 FT	131 FT
BRAID AND LIFT-EYE INSTALLATION	D BRING	$2^{20}1/2$ "[(3) INSTALL			2						P1			PIGTAIL	171283	171301	171284	171306	171543	171551	171560	171581	171588	171654	171681	171690	172224
												({ ∘ ° ∘ }))−2)	5 11	SBE PN	801140	801148	801150	801153	801293	801295	801301	801304	801307	801340	801352	801358	801514



